

Q SERIES SPEAKERS

MBQUART



- 6.5" Nomex PMI Composite Cone
- 40mm Teteron Silk Composite Tweeter
- High Definition Crossovers with Advanced "Q Control" For The Tweeter & Midrange with Variable Points Of Attenuation
- Flat Linear Response
- High Sensitivity
- Incredible Low Frequency Reproduction

QS216

6-1/2" Component Set • 170w Maximum / 80w Continual

****SPECIAL ORDER - ADDITIONAL SHIPPING CHARGES MAY APPLY****

REFERENCE SHALLOW MOUNT SUBWOOFERS

MBQUART



- Double Roll Reinforced Steel Frame
- 2.5" Voice Coils On Glass Fiber Former
- Injection Polypropylene Flat Piston Cone
- NBR Rubber Surround
- Single Flat Poly Cotton Spider with Woven Tinsel Lead Wire
- Custom Nickel Plated Push Terminals
- 10" Works In .5 cu ft, 12" Works In .7 cu ft

RLP254

10" Dual 4Ω Voice Coil • 600w Maximum / 300w RMS

RLP304

12" Dual 4Ω Voice Coil • 600w Maximum / 300w RMS

ONYX AMPLIFIERS

MBQUART



Class A/B Multi Channel Models

- 4/2 Ohm Stable
- Illuminated MB Quart Logo
- Variable Low Pass, High Pass, Bandpass Filter
- Built In System Diagnostics
- Digital D-Class Mono Block Models add:
- 4/2/1 Ohm Stable
- Bass EQ w/45Hz Bass Boost
- Variable Low Pass & Subsonic Filter
- Bass Remote Included

ONX1.1000D

1 x 475w @ 4Ω 1 x 750w @ 2Ω 1 x 1000w @ 1Ω

ONX1.1500D

1 x 500w @ 4Ω 1 x 1000w @ 2Ω 1 x 1500w @ 1Ω

ONX4.60

4 x 60w @ 4Ω 4 x 120w @ 2Ω 2 x 240w @ 4Ω

ONX4.80

4 x 80w @ 4Ω 4 x 160w @ 2Ω 2 x 320w @ 4Ω

ONX4.125

4 x 125w @ 4Ω 4 x 250w @ 2Ω 2 x 500w @ 4Ω

ONX80.4+500

4 x 80w + 1 x 250w @ 4Ω 4 x 160w + 1 x 375 @ 2Ω

ONYX SUBWOOFERS

MBQUART



- Gloss Black Polypropylene Cone
- NBR Rubber Surround
- Red NOMEX Spider Woven Tinsel Leads
- 2.5" Voice Coils
- Black Steel Frame
- Illuminated Dust Cap

ONX302

12" Dual 2Ω Voice Coil • 800w Maximum / 400w RMS

ONX304

12" Dual 4Ω Voice Coil • 800w Maximum / 400w RMS

ONYX SPEAKERS

MBQUART



- Piano Black 30mm WideSphere Tweeter Assembly
- Multiple Tweeter Mounting Options
- 0db / -3dB / -6dB Crossover Control
- Piano Black Polypropylene Cone
- Rugged Stamped Steel Chassis

ONX116

6-1/2" Coaxials • 100w Maximum / 50w RMS

ONX157T

5 x 7" Coaxials • 120w Maximum / 50w RMS

ONX169T

6 x 9" Coaxials • 140w Maximum / 60w RMS

ONX216

6-1/2" Component Set • 120w Maximum / 50w RMS

OTK30

30mm Onyx Tweeter Kit w/In-Line Crossover • 120w Maxx

FORMULA SUBWOOFERS

MBQUART



- Ultra Rigid Pressed Pulp Cone
- High Excursion Rubber Surround
- Woven Spider Tinsel Leads
- High Energy Magnet w/Cover
- Front Plate & Voice Coil Cooling

FWA304D

12" Dual 4Ω Voice Coil • 600w Maximum / 300w RMS

FORMULA SPEAKERS

MBQUART



- Polypropylene Woofer Cone
- Stamped Steel Chassis
- Woven Tinsel Leads
- Crossover with +/- 3dB Terminals
- 19mm Titanium Dome Tweeters

FKB116

6-1/2" Coaxials • 150w Maximum / 40w RMS

FKB157

5 x 7" / 6 x 8" Coaxials • 150w Maximum / 40w RMS

FTB169

6 x 9" 3-Way Speakers • 180w Maximum / 50w RMS

FSB216

6-1/2" Component Set • 150w Maximum / 40w RMS